

LUASLEKI



MOTOR: EAD100-220V

MOTOR ZA AUTOMATSKO OTVARANJE/ZATVARANJE VRATA DO 280kg





NIŽE U ORIGINALU

AC 220V/110V 280kg - Automatic Door Opener for aluminum or wooden Door

• Automatic Flat door systems with Pull arm or Push arm,

•Support 110V or 220V with a brushed motor

Power supply: 110V or 220V
Opening time: 3~7s / 90°
Opening and holding time: 1-30s

• Protection level: IP12D









MA-204T MA-204

Model No. EAD100

Below is detailed technical specification:





Model No.	EAD100 (A)	EAD100 (B)	EAD100 (C)	EAD100 (D)
An operator with arm	Pull arm	Push arm	Pull arm	Push arm
Power supply	220V	220V	110V	110V
Opening time	3~7s / 90°			
Opening and holding time	1-30s			
Temperature	-20°C~55°C			
Protection level	IP12D			
Dimensions	516x105x82mm			
Packing box	626x197x152mm			
Weight	8.5kg			

EAD100 is low energy automatic with a swing door opener that is activated by push buttons. This system operates in both automatic and manual modes, it makes the electronic door opener and closer highly adapts to voltage fluctuations between 110 or 220VAC $\pm 10\%$, more energy-saving and durable than an ordinary single input voltage. The simple yet secure system for areas such as offices, hospitals, elderly homes, banks, commercial locations, and much more.

It supports 2ways working mode:

- 1. standalone access controller, connect it to power, power on, then we could open it by remote control and close it automatically
- 2. Connect it with RFID door access control systems, Enter by Face, RFID, Pin code or Finger, and exit by EAB-10 or EAB-11 Non-touch button or MA-204T Microwave Sensor.

Main Features:

- 1. An advanced and reliable microprocessor controller is applied.
- 2. Brushless motor with self-locking, a long life span, and energy conservation.
- 3. Opening & Closing Speed adjustable.
- 4. Automatic/Lock/One Way/Half-open/Hold-open status can be set by remote key.
- 5. Opening and closing smooth with low noise.
- 6. Safety interlock and electric lock function.
- 7. Support multiple access control systems and Fire Alarm System
- 8. Auto-Reverse







KRAJ